

Article Number: 153148

2P/12V Socket (SAE J3082)



Categories	Socket
Standards	SAE J3082
Industries	Commercial vehicles , Agriculture

Electrical Details and Temperature Resistance

Temperature resistance [in °C]	-40.0 - 85.0
Voltage [in V]	12

Packaging and Order Details

Packaging	retail bag
-----------	------------

Design Features

Branding	neutral/without logo
Strain relief	stainless steel spring

Material

Contact insert color	black
Contact surface	nickel (Ni)
Cover insert color	red
Cover material	reinforced composite
Cover version	with seal
Housing color	black
Housing material	reinforced composite

Connectivity

Cable outlet	cable outlet 180° , grommet
Contact termination	screw contact
No. of poles	02
Outlet open or closed	n.a.

Norms and Standards

Protection	IP X9
------------	-------

Measures and Dimensions

American Wire Gauge (AWG)	4AWG cable
---------------------------	------------